

This program is very simple when you have an existing remote

You should stand near your Ditec motor or control box within 5 meters or between your gate and garage door(s).



- Step 1. Press **an existing remote** make sure if the old remote works.
- Step 2. Insert a paper clip or a needle into the underside tiny pore of your **existing remote** 5 seconds (see the figure on back of the box)



- Step 3. Press the button (with a dot) of your **new remote** 1 second.
 - Step 4. Wait for about 10 seconds.
- The programming is done, now you can test your new remote if works

NOTICE: if your old remote is not working, please do the following procedures



- ① Press the black program button inside the control box (can be opened by removing the cover) for 5 seconds
- ② Press the button shown 1 second
- ③ Wait for 10 seconds

How to delete existing code : for gate, press the little black program button (open the motor box, it is inside) until seeing the red light flashing slowly and release, and press the button again until seeing the light flashing really fast and release, then wait for 10 seconds. DO the same thing to the gate and garage door (the program button for garage should be on the receiver board)